

# CCS-USB

## The go-to software for all your camera control needs

Automatically set up your COM ports through connection to computer via USB. Control up to 7 primary cameras utilizing advanced SONY VISCA™ protocol and up to 255 cameras utilizing PELCO™ protocol. Compatible with Windows and Mac OSX™ operating systems.


**KEY FEATURES:**

**APPLICATIONS:**



LIVE PRODUCTION



WORSHIP



VIDEO CONFERENCE



MEDICAL



THEATER

## MAIN FEATURES


- SONY VISCA Compatible and work with most of major VISCA protocol products.
- Support PELCO Pan / Tilt / Zoom / Focus protocol.
- Control up to 7 VISCA control cameras and 255 third party control cameras.
- User friendly software interface.
- Support RS-232, RS-485, RS-422.
- USB interface for easy installation.
- Windows and MAC OS X compatible.
- Compact and rugged design.

## SPECIFICATIONS

<b>VIDEO</b>		<b>PHYSICAL</b>	
<b>Camera Interface</b>	RS-232C, RS-485/RS-422: Terminal Block Connector	<b>Camera Control</b>	RS-232C: 8 Pin Mini Din Connector RS-485/RS-422: Terminal Block Connector
<b>Protocol</b>	VISCA for Camera Setting up to 7 Cameras PELCO for Pan/Tilt/Zoom Control up to 255 Cameras	<b>Accessory</b>	CBL-RJ45 (RS232 to Cross-RJ45 converter cable)
<b>User Interface</b>	Graphic User interface	<b>Operation Temp</b>	32°F - 104°F
<b>PC Interface</b>	USB	<b>Dimension</b>	62m x 35m x 19mm / 2.44" x 1.37" x 0.74"
<b>Compatibility</b>	All VISCA Protocol Camera All PELCO Protocol Camera	<b>Weight</b>	50g / 0.11lb
<b>MAIN FUNCTIONS ON VISCA CONTROL</b>		<b>Power</b>	USB Powered
<b>Image</b>	Contrast, Saturation, Sharpness, Gamma		
<b>Exposure</b>	Auto, Shutter Priority, Iris Priority, Manual, Flicker-less		
<b>White Balance</b>	Auto, Manual, ATW		
<b>Back-light</b>	WDR, BLC		

*\*Specification are subject to change without notice.*

## PACKAGE CONTENTS



**DC 12v Power Supply & Sockets Adapter**



**CBL-RJ45 (RS-232C Cross RJ45 Converter Cable)**